TECHNICAL REPORT NO. CAM-110-9

(BRL CR NO. 7)

PROPAGATION OF
FIRST-ORDER ELECTROMAGNETIC DISCONTINUITIES
IN AN ISOTROPIC MEDIUM

Prepared by

Lehigh University
Center for the Application of Mathematics
Bethlehem, Pennsylvania

February 1970

BRL CR No. 7

Propagation of first-order electromagnetic discontinuities

in an isotropic medium.

by

R. Venkataraman

and

R. S. Rivlin

Center for the Application of Mathematics

Lehigh University

Bethlehem, Pa.

Propagation of first-order electromagnetic discontinuities

in an isotropic medium.

by

R. Venkataraman

and

R. S. Rivlin

Center for the Application of Mathematics

Lehigh University

Bethlehem, Pa.

Abstract

The propagation of a first-order electromagnetic disconti-
nuity is discussed. Expressions are obtained for the possible
velocities of propagation as functions of the field strengths
ahead of the surface of discontinuity. Expressions are also
obtained for the growth in the magnitude of the discontinuity
as the wave progresses.

1. Introduction.

In this paper we shall discuss the propagation of electro-
magnetic waves in which the fields are continuous with respect
to space and time, but where spatial and time deriatives may be
discontinuous on some surface. Such discontinuities are called
first-order discontinuities. Until recently studies of the
propagation of discontinuities of this type have been confined
to fluid dynamics (see, for example, Courant and Friedrichs[1]).
More recently, using a technique based on the compatibility
conditions at a moving surface of discontinuity, Thomas[2] has
studied the growth of elastic waves of this type in linear ma-
terials. Varley and Cumberbatch[3] have considered the more
general problem of a quasilinear, first order, system of hyper-
bolic equations using a variant of the method for a linear
system described in Courant and Hilbert[4]. In this paper we
apply the procedure of Varley and Cumberbatch to the study of
the propagation of first-order electromagnetic discontinuities
in a non-linear centrosymmetric isotropic material, for which
the electric displacement field depends only on the electric
field and the magnetic induction field depends only on the mag-
netic intensity field.

We obtain first the secular equation for the propagation
of a first-order electromagnetic discontinuity surface. We
find that there are, in general, two possible propagation
velocities in a specified forward direction and correspondingly
two possible polarization directions. Both the velocities and
directions of polarization depend on the magnetic induction field and
electric displacement field immediately ahead of the disconti-
nuity.

In §4, we obtain an expression for the growth of the
magnitude of the discontinuity as a surface of discontinuity
propagates. In §§5 and 6 this result is specialized to two

cases in which the fields ahead of the surface of discontinuity are uniform and constant. In one of these the magnetic induction field is taken normal to the surface of discontinuity and in the other, the electric displacement field is taken to be normal to this surface.

2. Propagating Surfaces.

In this section, we consider the propagation of an electro-magnetic wave for which the magnetic induction field B and elastic displacement field D are continuous, while their first derivatives, both with respect to space and time, may be dis-continuous across some surface. This singular surface is called a first-order singular surface.

Let x be the vector position of a generic point on this singular surface with respect to a fixed origin. Let

$$\phi(x,t) = 0 , \qquad (2.1)$$

for fixed t, be the equation of the singular surface at time t. We define α by

$$\alpha = \phi(x,t) , \qquad (2.2)$$

and assume that ϕ is a continuous function of x and of t, which has continuous first derivatives with respect to space and time. We also assume that $\partial\phi/\partial t \neq 0$ in some neighborhood of the propagating singular surface, i.e. $\alpha = 0$.

In view of the definition (2.2) of α, we see that α = constant describes a propagating surface, which is the singular surface if the constant is zero. Also, the variables x,α define a point on such a surface. Let $n(x,\alpha)$ denote the unit normal at the point x to the surface α = constant, drawn in the direction of propagation. Let V(>0) denote the speed of propagation of the surface. From the definition of the speed V of a moving surface at a point as the speed with which the surface moves normal to itself at that point, we have

$$V = n \cdot \frac{dx}{dt} , \qquad (2.3)$$

where

$$\underset{\sim}{n} = \nabla\phi/(\nabla\phi\cdot\nabla\phi)^{1/2} \quad . \tag{2.4}$$

Now, from (2.2), we have for the moving surface α = constant,

$$\nabla\phi \cdot \frac{d\underset{\sim}{x}}{dt} + \frac{\partial\phi}{\partial t} = 0 \quad . \tag{2.5}$$

Multiplying (2.5) throughout by $\underset{\sim}{n}$ and using (2.3) and (2.4), we obtain

$$\frac{\underset{\sim}{n}}{V} = - \frac{\nabla\phi}{\partial\phi/\partial t} \quad . \tag{2.6}$$

Now, any function f, say, of $\underset{\sim}{x}$ and t may also be regarded as a function $\bar{f}$, say, of $\underset{\sim}{x}$ and α, where α is defined by (2.2). We then have

$$f(\underset{\sim}{x},t) = \bar{f}(\underset{\sim}{x},\alpha) \quad . \tag{2.7}$$

Whence

$$\frac{\partial f}{\partial t} = \frac{\partial\bar{f}}{\partial\alpha}\frac{\partial\alpha}{\partial t} = \frac{\partial\bar{f}}{\partial\alpha}\frac{\partial\phi}{\partial t} \quad . \tag{2.8}$$

We define the operator $\bar{\nabla}$ as the spatial gradient, holding α constant. It follows, from (2.7), that

$$\nabla f = \nabla\bar{f} = \bar{\nabla}\bar{f} + \frac{\partial\bar{f}}{\partial\alpha}\nabla\phi \quad . \tag{2.9}$$

With (2.6) and (2.8), this yields

$$\nabla f = \overline{\nabla} f - \frac{n}{V} \frac{\partial \overline{f}}{\partial \alpha} \frac{\partial \phi}{\partial t} = \overline{\nabla} f - \frac{n}{V} \frac{\partial f}{\partial t} \quad . \tag{2.10}$$

Thus, we may take the operator $\overline{\nabla}$ as

$$\overline{\nabla} = \nabla + \frac{n}{V} \frac{\partial}{\partial t} \quad . \tag{2.11}$$

Here we may point out that the operator $\overline{\nabla}$ is a surface operator on the surface $\phi = 0$ since by the choice of the new set of coordinates, the variables involved in the differentiation correspond to a displacement on the surface[4].

3. The Secular Equation.

In the absence of free charges, Maxwell's equations may be written as

$$\nabla \times \underset{\sim}{E} + \partial \underset{\sim}{B}/\partial t = 0 \quad ,$$

$$\nabla \times \underset{\sim}{H} - \partial \underset{\sim}{D}/\partial t = 0 \quad , \tag{3.1}$$

where $\underset{\sim}{E}$ and $\underset{\sim}{H}$ are the electric and magnetic intensity fields respectively.

We shall consider that the medium in which the wave is propagating is isotropic, centrosymmetric and non-dissipative and that $\underset{\sim}{E}$ is determined only by $\underset{\sim}{D}$ and $\underset{\sim}{H}$ is determined only by $\underset{\sim}{B}$. It follows that the constitutive equations take the forms

$$\underset{\sim}{E} = \varepsilon (\underset{\sim}{D} \cdot \underset{\sim}{D}) \underset{\sim}{D} \quad \text{and} \quad \underset{\sim}{H} = \mu (\underset{\sim}{B} \cdot \underset{\sim}{B}) \underset{\sim}{B} \quad , \tag{3.2}$$

where ε and μ are scalar functions of the indicated arguments.

Introducing (3.2) into (3.1), we obtain

$$\nabla \varepsilon \times \underset{\sim}{D} + \varepsilon \nabla \times \underset{\sim}{D} + \frac{\partial \underset{\sim}{B}}{\partial t} = \varepsilon' \nabla (\underset{\sim}{D} \cdot \underset{\sim}{D}) \times \underset{\sim}{D} + \varepsilon \nabla \times \underset{\sim}{D} + \frac{\partial \underset{\sim}{B}}{\partial t} = 0$$

and $\tag{3.3}$

$$\nabla \mu \times \underset{\sim}{B} + \mu \nabla \times \underset{\sim}{B} - \frac{\partial \underset{\sim}{D}}{\partial t} = \mu' \nabla (\underset{\sim}{B} \cdot \underset{\sim}{B}) \times \underset{\sim}{B} + \mu \nabla \times \underset{\sim}{B} - \frac{\partial \underset{\sim}{D}}{\partial t} = 0 \quad ,$$

where $\varepsilon' = \partial \varepsilon / \partial (\underset{\sim}{D} \cdot \underset{\sim}{D})$ and $\mu' = \partial \mu / \partial (\underset{\sim}{B} \cdot \underset{\sim}{B})$.

We bear in mind the known vector identity

$$\nabla (\underset{\sim}{D} \cdot \underset{\sim}{D}) = 2 [(\underset{\sim}{D} \cdot \nabla) \underset{\sim}{D} + \underset{\sim}{D} \times (\nabla \times \underset{\sim}{D})] \quad . \tag{3.4}$$

Substituting from (3.4) and (2.11) in (3.3)$_1$, we obtain

$$\varepsilon \underset{\sim}{n} \times \frac{\partial \underset{\sim}{D}}{\partial t} + 2\varepsilon'(\underset{\sim}{D} \cdot \frac{\partial \underset{\sim}{D}}{\partial t})(\underset{\sim}{n} \times \underset{\sim}{D}) - V \frac{\partial \underset{\sim}{B}}{\partial t}$$

$$= 2\varepsilon'V[(\underset{\sim}{D} \cdot \underset{\sim}{\overline{\nabla}})\underset{\sim}{D} \times \underset{\sim}{D} + \{\underset{\sim}{D} \times (\underset{\sim}{\overline{\nabla}} \times \underset{\sim}{D})\} \times \underset{\sim}{D}] + \varepsilon V \underset{\sim}{\overline{\nabla}} \times \underset{\sim}{D} \quad . \tag{3.5}$$

Similarly, from (3.3)$_2$ we obtain

$$\mu \underset{\sim}{n} \times \frac{\partial \underset{\sim}{B}}{\partial t} + 2\mu'(\underset{\sim}{B} \cdot \frac{\partial \underset{\sim}{B}}{\partial t})(\underset{\sim}{n} \times \underset{\sim}{B}) + V \frac{\partial \underset{\sim}{D}}{\partial t}$$

$$= 2\mu'V[(\underset{\sim}{B} \cdot \underset{\sim}{\overline{\nabla}})\underset{\sim}{B} \times \underset{\sim}{B} + \{\underset{\sim}{B} \times (\underset{\sim}{\overline{\nabla}} \times \underset{\sim}{B})\} \times \underset{\sim}{B}] + \mu V \underset{\sim}{\overline{\nabla}} \times \underset{\sim}{B} \quad . \tag{3.6}$$

We now introduce the assumption that $\underset{\sim}{B}$ and $\underset{\sim}{D}$ are continuous at the moving surface $\phi = 0$. It follows that their tangential derivatives $\underset{\sim}{\overline{\nabla}}B$, $\underset{\sim}{\overline{\nabla}}D$, $\underset{\sim}{\overline{\nabla}} \times B$ and $\underset{\sim}{\overline{\nabla}} \times D$ are also continuous across the surface.

We denote by $\underset{\sim}{b}$ and $\underset{\sim}{d}$ the jumps in $\partial B/\partial t$ and $\partial D/\partial t$ as we cross the surface $\phi = 0$ in the direction of $\underset{\sim}{n}$; thus

$$\underset{\sim}{b} = [\partial B/\partial t] \quad , \quad \underset{\sim}{d} = [\partial D/\partial t] \quad . \tag{3.7}$$

With (3.7) we obtain, from (3.5) and (3.6), on $\phi = 0$

$$\varepsilon \underset{\sim}{n} \times \underset{\sim}{d} + 2\varepsilon'(\underset{\sim}{D} \cdot \underset{\sim}{d})(\underset{\sim}{n} \times \underset{\sim}{D}) - V\underset{\sim}{b} = 0$$

and

$$\tag{3.8}$$

$$\mu \underset{\sim}{n} \times \underset{\sim}{b} + 2\mu'(\underset{\sim}{B} \cdot \underset{\sim}{b})(\underset{\sim}{n} \times \underset{\sim}{B}) + V\underset{\sim}{d} = 0 \quad .$$

From (3.8), we obtain

$$\underset{\sim}{n} \cdot \underset{\sim}{b} = 0 \quad \text{and} \quad \underset{\sim}{n} \cdot \underset{\sim}{d} = 0 \quad . \tag{3.9}$$

Thus, the jumps $\underset{\sim}{b}$ and $\underset{\sim}{d}$ are tangential to the surface $\phi = 0$. Now, eliminating $\underset{\sim}{d}$ from (3.8), we obtain on $\phi = 0$

$$\mu \varepsilon \underset{\sim}{n} \times (\underset{\sim}{n} \times \underset{\sim}{b}) + 2\mu' \varepsilon (\underset{\sim}{B} \cdot \underset{\sim}{b}) \{\underset{\sim}{n} \times (\underset{\sim}{n} \times \underset{\sim}{B})\}$$

$$+ 2\varepsilon'(\underset{\sim}{n} \times \underset{\sim}{D})[\mu \underset{\sim}{D} \cdot (\underset{\sim}{n} \times \underset{\sim}{b}) + 2\mu'(\underset{\sim}{B} \cdot \underset{\sim}{b})\{\underset{\sim}{D} \cdot (\underset{\sim}{n} \times \underset{\sim}{B})\}] + V^2 \underset{\sim}{b} = 0 \quad . \tag{3.10}$$

We introduce the notation

$$\underset{\sim}{B} = \underset{\sim}{B}_t + \underset{\sim}{B}_n \quad , \quad \underset{\sim}{D} = \underset{\sim}{D}_t + \underset{\sim}{D}_n \quad , \tag{3.11}$$

where $\underset{\sim}{B}_t$ and $\underset{\sim}{D}_t$ are tangential to the surface $\phi = 0$ and $\underset{\sim}{B}_n$ and $\underset{\sim}{D}_n$ are normal to it. We also write

$$\underset{\sim}{J} = \underset{\sim}{n} \times \underset{\sim}{D}_t \quad . \tag{3.12}$$

Using (3.11), (3.12) and (3.9)$_1$ in (3.10), we obtain

$$(V^2 - \mu\varepsilon)\underset{\sim}{b} - 2\mu'\varepsilon(\underset{\sim}{B}_t \cdot \underset{\sim}{b})\underset{\sim}{B}_t$$

$$-2\varepsilon'\underset{\sim}{J}[\mu(\underset{\sim}{b} \cdot \underset{\sim}{J}) + 2\mu'(\underset{\sim}{B}_t \cdot \underset{\sim}{b})(\underset{\sim}{B}_t \cdot \underset{\sim}{J})] = 0 \quad . \tag{3.13}$$

Forming the dot product of (3.13) with $\underset{\sim}{B}_t$, we obtain

$$[(V^2 - \mu\varepsilon) - 2\mu'\varepsilon(\underset{\sim}{B}_t \cdot \underset{\sim}{B}_t) - 4\mu'\varepsilon'(\underset{\sim}{B}_t \cdot \underset{\sim}{J})^2](\underset{\sim}{B}_t \cdot \underset{\sim}{b})$$

$$= 2\mu\varepsilon'(\underset{\sim}{b} \cdot \underset{\sim}{J})(\underset{\sim}{B}_t \cdot \underset{\sim}{J}) \quad . \tag{3.14}$$

Forming the dot product of (3.13) with $\underset{\sim}{J}$, we obtain

$$[-2\mu'\varepsilon(\underset{\sim}{J}\cdot\underset{\sim}{B}_t) - 4\mu'\varepsilon'(\underset{\sim}{B}_t\cdot\underset{\sim}{J})(\underset{\sim}{J}\cdot\underset{\sim}{J})](\underset{\sim}{B}_t\cdot\underset{\sim}{b})$$

$$= [(\mu\varepsilon-V^2) + 2\mu\varepsilon'(\underset{\sim}{J}\cdot\underset{\sim}{J})](\underset{\sim}{b}\cdot\underset{\sim}{J}) \quad . \tag{3.15}$$

Eliminating $\underset{\sim}{b}$ from (3.14) and (3.15) and using the notation

$$x = V^2 - \mu\varepsilon \quad , \tag{3.16}$$

we obtain

$$x^2 - x \; [2\mu'\{\varepsilon(\underset{\sim}{B}_t\cdot\underset{\sim}{B}_t) + 2\varepsilon'(\underset{\sim}{B}_t\cdot\underset{\sim}{J})^2\} + 2\mu\varepsilon'(\underset{\sim}{J}\cdot\underset{\sim}{J})]$$

$$+ 4\mu\mu'\varepsilon\varepsilon'\{(\underset{\sim}{J}\cdot\underset{\sim}{J})(\underset{\sim}{B}_t\cdot\underset{\sim}{B}_t) - (\underset{\sim}{J}\cdot\underset{\sim}{B}_t)^2\} = 0 \quad . \tag{3.17}$$

From (3.16) and (3.17), we obtain the two solutions for V^2:

$$V^2 = \mu\varepsilon + \mu'[\varepsilon(\underset{\sim}{B}_t\cdot\underset{\sim}{B}_t) + 2\varepsilon'(\underset{\sim}{J}\cdot\underset{\sim}{B}_t)^2] + \mu\varepsilon'(\underset{\sim}{J}\cdot\underset{\sim}{J})$$

$$\pm\{[\mu'\{\varepsilon(\underset{\sim}{B}_t\cdot\underset{\sim}{B}_t) + 2\varepsilon'(\underset{\sim}{J}\cdot\underset{\sim}{B}_t)^2\} + \mu\varepsilon'(\underset{\sim}{J}\cdot\underset{\sim}{J})]^2$$

$$- 4\mu\mu'\varepsilon\varepsilon'[(\underset{\sim}{J}\cdot\underset{\sim}{J})(\underset{\sim}{B}_t\cdot\underset{\sim}{B}_t) - (\underset{\sim}{J}\cdot\underset{\sim}{B}_t)^2]^{1/2} \quad . \tag{3.18}$$

V^2 is real and positive if and only if

$$[\mu'\{\varepsilon(\underset{\sim}{B}_t\cdot\underset{\sim}{B}_t) + 2\varepsilon'(\underset{\sim}{J}\cdot\underset{\sim}{B}_t)^2\} + \mu\varepsilon'(\underset{\sim}{J}\cdot\underset{\sim}{J})^2]^2$$

$$\geqslant 4\mu\mu'\varepsilon\varepsilon'[(\underset{\sim}{J}\cdot\underset{\sim}{J})(\underset{\sim}{B}_t\cdot\underset{\sim}{B}_t) - (\underset{\sim}{J}\cdot\underset{\sim}{B}_t)^2] \tag{3.19}$$

and $\mu\varepsilon > 0$. In this case we see that for given $\underset{\sim}{n}$, $\underset{\sim}{B}_t$ and $\underset{\sim}{D}_t$, there are two possible real speeds of propagation in the

forward direction. Propagation in the opposite direction with equal speeds is also possible.

Provided that V^2 is a simple root of the equation (3.17), i.e. the greater than sign in (3.19) is valid, we can determine the direction of polarization of $\underset{\sim}{b}$ from equation (3.10). Then the direction of polarization of $\underset{\sim}{d}$ can be determined from equation $(3.8)_2$.

4. Growth Equation.

In this section we shall derive a differential equation governing the change in magnitude of the discontinuity. In order to do this it is more convenient to refer all equations to a rectangular cartesian reference system and to use indicial notation. With this notation, we obtain, by differentiating equations (3.3) with respect to t,

$$e_{ijk}\{P_{k\ell} \frac{\partial}{\partial t}(\frac{\partial D_\ell}{\partial x_j}) + Q_{nk\ell} \frac{\partial D_n}{\partial t} \frac{\partial D_\ell}{\partial x_j}\} + \frac{\partial^2 B_i}{\partial t^2} = 0 \quad ,$$

<div align="right">(4.1)</div>

$$e_{ijk} R_{k\ell} \frac{\partial}{\partial t}(\frac{\partial B_\ell}{\partial x_j}) + S_{nk\ell} \frac{\partial B_n}{\partial t} \frac{\partial B_\ell}{\partial x_j}\} - \frac{\partial^2 D_i}{\partial t^2} = 0 \quad ,$$

where

$$P_{k\ell} = \varepsilon\delta_{k\ell} + 2\varepsilon'D_kD_\ell \quad ,$$

$$R_{k\ell} = \mu\delta_{k\ell} + 2\mu'B_kB_\ell \quad ,$$

<div align="right">(4.2)</div>

$$Q_{nk\ell} = \partial P_{k\ell}/\partial D_n = 2\varepsilon'D_n\delta_{k\ell} + 4\varepsilon''D_nD_RD_\ell + 2\varepsilon'D_k\delta_{\ell n}$$
$$+ 2\varepsilon'D_\ell\delta_{kn} \quad ,$$

$$S_{nk\ell} = \partial R_{k\ell}/\partial B_n = 2\mu'B_n\delta_{k\ell} + 4\mu''B_nB_kB_\ell + 2\mu'B_k\delta_{\ell n}$$
$$+ 2\mu'B_\ell\delta_{kn} \quad ,$$

and e_{ijk} denotes the alternating symbol.

We now change the independent variables from x_i, t to x_i, α. In indicial notation, the relation (2.10) may be expressed as

$$\frac{\partial}{\partial x_j} = \left(\frac{\partial}{\partial x_j}\right)_\alpha - \frac{n_j}{V}\frac{\partial}{\partial t} \quad , \tag{4.3}$$

whence

$$\frac{\partial}{\partial t}\left(\frac{\partial}{\partial x_j}\right) = \frac{\partial}{\partial x_j}\left(\frac{\partial}{\partial t}\right) = \left(\frac{\partial}{\partial x_j}\right)_\alpha \frac{\partial}{\partial t} - \frac{n_j}{V}\frac{\partial^2}{\partial t^2} \quad . \tag{4.4}$$

Introducing (4.3) and (4.4) into (4.1), we obtain

$$e_{ijk}P_{k\ell}n_j\frac{\partial^2 D_\ell}{\partial t^2} - V\frac{\partial^2 B_i}{\partial t^2} = Ve_{ijk}\{P_{k\ell}\left(\frac{\partial}{\partial x_j}\right)_\alpha \frac{\partial D_\ell}{\partial t}$$

$$+ Q_{nk\ell}\frac{\partial D_n}{\partial t}\left(\left(\frac{\partial D_\ell}{\partial x_j}\right)_\alpha - \frac{n_j}{V}\frac{\partial D_\ell}{\partial t}\right)\}$$

$$\tag{4.5}$$

and

$$e_{ijk}R_{k\ell}n_j\frac{\partial^2 B_\ell}{\partial t^2} + V\frac{\partial^2 D_i}{\partial t^2} = Ve_{ijk}\{R_{k\ell}\left(\frac{\partial}{\partial x_j}\right)_\alpha \frac{\partial B_\ell}{\partial t}$$

$$+ S_{nk\ell}\frac{\partial B_n}{\partial t}\left(\left(\frac{\partial B_\ell}{\partial x_j}\right)_\alpha - \frac{n_j}{V}\frac{\partial B_\ell}{\partial t}\right)\} \quad .$$

Eliminating $V\,\partial^2 D_i/\partial t^2$ from (4.5), we obtain

$$-(a_{is}+V^2\delta_{is})\frac{\partial^2 B_s}{\partial t^2} = e_{ijk}\{V^2 P_{k\ell}\left(\frac{\partial}{\partial x_j}\right)_\alpha \left(\frac{\partial D_\ell}{\partial t}\right)$$

$$+ V^2 Q_{nk\ell}\frac{\partial D_n}{\partial t}\left(\left(\frac{\partial D_\ell}{\partial x_j}\right)_\alpha - \frac{n_j}{V}\frac{\partial D_\ell}{\partial t}\right)$$

$$\tag{4.6}$$

$$-Ve_{\ell mn}P_{k\ell}R_{ns}n_j\left(\frac{\partial}{\partial x_m}\right)_\alpha\left(\frac{\partial B_s}{\partial t}\right)$$

$$-Ve_{\ell mn}P_{k\ell}S_{pns}n_j\left(\left(\frac{\partial B_s}{\partial x_m}\right)_\alpha\frac{\partial B_p}{\partial t} - \frac{n_m}{V}\frac{\partial B_s}{\partial t}\frac{\partial B_p}{\partial t}\right)\} \quad ,$$

where

$$a_{is} = e_{ijk}e_{\ell mn}P_{k\ell}R_{ns}n_jn_m \quad . \qquad\qquad (4.7)$$

Using square brackets to denote the jump in a quantity across the surface of discontinuity, we have

$$\left[\frac{\partial D_n}{\partial t}\frac{\partial D_\ell}{\partial t}\right] = \left[\frac{\partial D_n}{\partial t}\right]\left[\frac{\partial D_\ell}{\partial t}\right] + \left[\frac{\partial D_n}{\partial t}\right]\left(\frac{\partial D_\ell}{\partial t}\right)_o + \left[\frac{\partial D_\ell}{\partial t}\right]\left(\frac{\partial D_n}{\partial t}\right)_o \quad , \quad (4.8)$$

where $(\partial D_n/\partial t)_o$ denotes the value of $\partial D_n/\partial t$ immediately in front of the wave. Also, we note that $P_{k\ell}$, $Q_{nk\ell}$, $R_{k\ell}$ and $S_{nk\ell}$ are continuous across the surface of discontinuity.

Using these results, we obtain from (4.6), with the notation $b_i = [\partial B_i/\partial t]$, $d_i = [\partial D_i/\partial t]$,

$$-(a_{is}+V^2\delta_{is})\left[\frac{\partial^2 B_s}{\partial t^2}\right] = e_{ijk}\{V^2 P_{k\ell}\left(\frac{\partial d_\ell}{\partial x_j}\right)_\alpha$$

$$+ V^2 Q_{nk\ell}\{\left(\frac{\partial D_\ell}{\partial x_j}\right)_\alpha d_n - \frac{n_j}{V}\left(d_nd_\ell\right.$$

$$+ \left(\frac{\partial D_\ell}{\partial t}\right)_o d_n + \left(\frac{\partial D_n}{\partial t}\right)_o d_\ell\right)\}$$

$$- Ve_{\ell mn}P_{k\ell}R_{ns}n_j\left(\frac{\partial b_s}{\partial x_m}\right)_\alpha$$

$$- Ve_{\ell mn}P_{k\ell}S_{pns}n_j\{(\frac{\partial B_s}{\partial x_m})_\alpha \, b_p - \frac{n_m}{V}(b_s b_p$$

$$+ (\frac{\partial B_p}{\partial t})_o \, b_s + (\frac{\partial B_s}{\partial t})_o \, b_p)\}\} \quad . \tag{4.9}$$

We now introduce the notation

$$b_s = \sigma r_s \quad , \tag{4.10}$$

where r_s is a unit vector in the direction of b_s. With (4.10) and (4.2), equation $(3.8)_2$ becomes

$$Vd_\ell = -R_{ns}e_{\ell mn}n_m b_s = -R_{ns}e_{\ell mn}n_m r_s \sigma \quad . \tag{4.11}$$

Using this result to substitute for Vd_ℓ in (4.9), we obtain,

$$-(a_{is}+V^2\delta_{is})[\frac{\partial^2 B_s}{\partial t^2}] = L_i + M_i\sigma + N_i\sigma^2 \quad , \tag{4.12}$$

where

$$L_i = -Ve_{ijk}e_{\ell mn}P_{k\ell}R_{ns}r_s\{n_m(\frac{\partial\sigma}{\partial x_j})_\alpha + n_i(\frac{\partial\sigma}{\partial x_m})_\alpha\} \quad ,$$

$$M_i = -V^2 e_{ijk}e_{\ell mn}P_{k\ell}(\frac{\partial}{\partial x_j})_\alpha (\frac{1}{V}R_{ns}n_m r_s)$$

$$+e_{ijk}Q_{nk\ell}R_{tp}n_s r_p\{-e_{nst}V(\frac{\partial D_\ell}{\partial x_j})_\alpha$$

$$+e_{nst}n_j(\frac{\partial D_\ell}{\partial t})_o + e_{\ell st}n_j(\frac{\partial D_n}{\partial t})_o\} \tag{4.13}$$

$$-Ve_{ijk}e_{\ell mn}P_{k\ell}n_j\{R_{ns}(\frac{\partial r_s}{\partial x_m})_\alpha$$

$$+S_{pns}[(\frac{\partial B_s}{\partial x_m})_\alpha\ r_p - \frac{n_m}{V}\ r_s(\frac{\partial B_p}{\partial t})_o - \frac{n_m}{V}\ r_p(\frac{\partial B_s}{\partial t})_o]\}\ ,$$

$$N_i = -V^{-1}e_{ijk}e_{nst}e_{\ell ab}Q_{nk\ell}R_{tp}R_{bc}n_j n_a n_s r_p r_c$$

$$+e_{ijk}e_{\ell mn}P_{k\ell}S_{pns}n_j n_m r_s r_p\ \ .$$

In our present notation $(3.8)_1$ may be written

$$Vb_i = e_{ijk}P_{k\ell}n_j d_\ell\ \ . \tag{4.14}$$

With (4.11), we obtain

$$(a_{is}+V^2\delta_{is})b_s = 0\ \ , \tag{4.15}$$

where a_{is} is given by (4.7). We define a unit vector ℓ_i by

$$\ell_i(a_{is}+V^2\delta_{is}) = 0\ \ . \tag{4.16}$$

Multiplying (4.12) throughout by ℓ_i and using (4.16), we obtain

$$L + M\sigma + N\sigma^2 = 0\ \ , \tag{4.17}$$

where L, M and N are defined by

$$(L,M,N) = \ell_i(L_i,M_i,N_i)\ \ . \tag{4.18}$$

Introducing (4.7) and (4.10) into (4.15) and differentiating with respect to n_p, we obtain

$$\{e_{ijk}e_{\ell mn}P_{k\ell}R_{ns}(\delta_{pj}n_m + \delta_{pm}n_j) + 2V\frac{\partial V}{\partial n_p}\delta_{is}\}r_s$$

$$+ (e_{ijk}e_{\ell mn}P_{k\ell}R_{ns}n_j n_m + V^2\delta_{is})\frac{\partial r_s}{\partial n_p} = 0 \quad . \qquad (4.19)$$

Multiplying throughout by ℓ_i and bearing in mind (4.16) and (4.7), we obtain

$$e_{ijk}e_{\ell mn}P_{k\ell}R_{ns}(\delta_{pj}n_m + \delta_{pm}n_j)\ell_i r_s = -2V\frac{\partial V}{\partial n_p}\ell_i r_i \quad . \qquad (4.20)$$

Since a_{is}, defined by (4.7), is homogeneous of second degree in n_i and V is determined by the discriminant of equation (4.15), it follows that V is homogeneous of first degree in n_i. Therefore,

$$V = n_p \, \partial V/\partial n_p \quad . \qquad (4.21)$$

Now, suppose a point x_p depends on t in such a manner that it always lies on the moving surface of discontinuity. Then its velocity is dx_p/dt. The velocity of the surface normal to itself is V, which is therefore given by

$$V = n_p \, dx_p/dt \quad . \qquad (4.22)$$

From (4.21) and (4.22), we obtain

$$n_p \, \partial V/\partial n_p = n_p dx_p/dt \quad . \qquad (4.23)$$

A possible choice for the dependence of x_p on t which satisfies the condition that x_p shall always be on the surface of discontinuity is that for which

$$dx_p/dt = \partial V/\partial n_p \quad . \tag{4.24}$$

We shall make this choice* and calculate the growth in the magnitude of the singularity as we move along the locus of x_p.

From $(4.13)_1$, (4.18), (4.20) and (4.24), we obtain

$$L = 2V^2 \frac{\partial V}{\partial n_p}(\frac{\partial \sigma}{\partial x_p})_\alpha \ell_i r_i = 2V^2 \frac{d\sigma}{dt} \ell_i r_i \quad . \tag{4.25}$$

We introduce (4.25) into equation (4.17) and make the transformation

$$\sigma = 1/u \quad . \tag{4.26}$$

We obtain

$$\frac{du}{dt} = \overline{M}u + \overline{N} \quad , \tag{4.27}$$

where

$$\overline{M} = M/2V^2\ell_i r_i \quad , \quad \overline{N} = N/2V^2\ell_i r_i \quad . \tag{4.28}$$

This equation has the general solution

$$u = \frac{1}{\sigma} = e^{\int \overline{M}dt} \left\{ C + \int \overline{N}\, e^{-\int \overline{M}dt} dt \right\} \quad , \tag{4.29}$$

---

*In this case the locus of x_p is, in fact, a bicharacteristic of the secular equation $|a_{is}+V^2\delta_{is}| = 0$.

where C is a constant of integration.

We see that if the fields $\underset{\sim}{B}$ and $\underset{\sim}{D}$ are known before passage of the surface of discontinuity, the velocity of such a surface, propagating in a given direction, can be determined from (3.18). $P_{k\ell}$ and $R_{k\ell}$ defined by (4.2) can be determined and hence a_{is} can be determined. r_i can then be calculated from (4.15) and (4.10), and ℓ_i from (4.16). Then, $\overline{M}$ and $\overline{N}$ can be determined from (4.28), (4.18) and (4.13).

5. <u>Special case: magnetic induction field ahead of wave in direction of propagation.</u>

We now assume that the fields ahead of the moving surface of discontinuity are uniform. This implies that the speeds of propagation V given by (3.18) are constant. It then follows, from (4.15), that $\underset{\sim}{b}$ has a constant orientation (i.e. $\underset{\sim}{r}$ is a constant) and, from (4.16), that the unit vector $\underset{\sim}{\ell}$ is constant. We see, from (4.13), that in this case $M_i = 0$ and N_i is constant. Then, from (4.18), $M = 0$ and N is constant. We then obtain from (4.27) or (4.29)

$$u = \frac{1}{\sigma} = \overline{N}t + \frac{1}{\sigma_0} \, , \tag{5.1}$$

where σ_0 is the value of σ when $t = 0$. The jump magnitude σ increases or decreases accordingly as $\overline{N}$ is negative or positive.

In the particular case when the direction of propagation is in the 1-direction and the applied magnetic induction field into which the wave propagates is also in the 1-direction, we have

$$n_i = \delta_{i1} \quad \text{and} \quad B_i = B\delta_{i1} \, . \tag{5.2}$$

Introducing (5.1) into (3.18), we have since $\underset{\sim}{B}_t = 0$,

$$V^2 = \mu\varepsilon \quad \text{or} \quad V^2 = \mu\varepsilon + 2\mu\varepsilon'(D_2^2 + D_3^2) \, . \tag{5.3}$$

Corresponding to the first of these results, we obtain

$$\underset{\sim}{r} = (D_2^2 + D_3^2)^{-1/2} (0, D_2, D_3) \tag{5.4}$$

and corresponding to the second, we have

$$r = (D_2^2 + D_3^2)^{-1/2} (0, -D_3, D_2) \quad . \tag{5.5}$$

The directions of polarization of the $\underset{\sim}{b}$ vectors associated with the two waves are perpendicular to each other.

Again, for the wave corresponding to the first of the solutions (5.3), we find that $\bar{N} = 0$, so that the discontinuity propagates unchanged.

We now consider the wave corresponding to the second of the solutions (5.3). Introducing (5.2) into (4.2)$_2$, we obtain

$$R_{ns} = \mu \delta_{ns} + 2\mu' B^2 \delta_{n1} \delta_{s1} \quad . \tag{5.6}$$

From (4.2)$_1$, (4.7), (5.2) and (5.6) we see that a_{is} is symmetric for interchange of i and s. Hence, with (5.5),

$$\ell_i = r_i = (D_2^2 + D_3^2)^{-1/2} (-D_3 \delta_{i2} + D_2 \delta_{i3}) \quad . \tag{5.7}$$

From (4.18) and (4.13)$_3$, we obtain, using (5.2),

$$N = -V^{-1} e_{i1k} e_{n1t} e_{\ell1b} Q_{nk\ell} R_{tp} R_{bc} r_p r_c \ell_i$$

$$+ e_{i1k} e_{\ell1n} P_{k\ell} S_{pns} r_s r_p \ell_i \quad . \tag{5.8}$$

Introducing the expressions (5.7) for r_i and ℓ_i into (5.8) and using (5.6), (4.2) and (5.2), we obtain, with (5.3)$_2$ and (4.28)$_2$

$$\bar{N} = -\frac{\mu^2 (3\varepsilon' + 2\varepsilon'' D^2) D}{(\mu\varepsilon + 2\mu\varepsilon' D^2)^{5/2}} \quad , \tag{5.9}$$

where $D = (D_2^2 + D_3^2)^{1/2}$ is the magnitude of the component of the electric displacement field normal to the direction of propagation. (In carrying out the calculation, we find that the second term on the right hand side of (5.8) is zero.) In the case when $D = 0$, the two waves with velocities given by (5.3) have the same speeds and can be propagated with arbitrary direction of polarization in the 23-plane.

6. Special case: electric displacement field ahead of wave in direction of propagation.

We again assume that the fields ahead of the moving surface of discontinuity are uniform, so that (5.1) still applies. We again take the 1-direction as the direction of propagation, but now assume that the electric displacement field is in the 1-direction, so that

$$n_i = \delta_{i1} \quad \text{and} \quad D_i = D\delta_{i1} \; . \tag{6.1}$$

It follows from (3.12) and (6.1) that

$$\underset{\sim}{J} = 0 \; . \tag{6.2}$$

Introducing this result into (3.18) we obtain

$$V^2 = \mu\varepsilon \quad \text{or} \quad V^2 = \mu\varepsilon + 2\mu'\varepsilon \; \underset{\sim}{B}_t \cdot \underset{\sim}{B}_t \; . \tag{6.3}$$

Corresponding to the first of these results, we have

$$\underset{\sim}{r} = (B_2^2 + B_3^2)^{-1/2} (0, -B_3, B_2) \tag{6.4}$$

and corresponding to the second of these results, we have

$$\underset{\sim}{r} = (B_2^2 + B_3^2)^{-1/2} (0, B_2, B_3) \; . \tag{6.5}$$

From (6.4) and (6.5) it follows that the directions of polarization of the electric vectors for the two waves are perpendicular.

For the wave corresponding to the first of the solutions (6.3), $N = 0$, so that, from (5.1), the discontinuity propagates unchanged.

We now consider the wave corresponding to the second of the solutions (6.3). As in §5, we again obtain the expression (5.8) for N. Introducing (6.1) into (4.2)$_1$, we obtain

$$P_{k\ell} = \varepsilon\delta_{k\ell} + 2\varepsilon'D^2\delta_{k1}\delta_{\ell1}. \qquad (6.6)$$

Proceeding in a manner analogous to that used in the previous section, we find that

$$N = -\frac{B(3\mu'+2\mu''B^2)}{\mu\varepsilon + 2\mu'\varepsilon B^2}, \qquad (6.7)$$

where $B = (B_2^2+B_3^2)^{1/2}$ is the magnitude of the component of the magnetic induction field normal to the direction of propagation. (In carrying out the calculation, we find that the first term on the right hand side of (5.8) is zero.)

Acknowledgement

References

1. Courant, R. and Friedrichs, K. O. "Supersonic Flow and Shock Waves", Interscience Publishers, New York, N.Y., 1948.

2. Thomas, T. Y. "Plastic Flow and Fracture in Solids", Academic Press, New York, 1961.

3. Varley, E. and Cumberbatch, E., Jour. Inst. Maths. Applicn. $\underline{1}$, 101, 1965.

4. Courant, R. and Hilbert, D. "Methods of Mathematical Physics II", Interscience Publishers, New York, 1962.

No. of Copies	Organization
20	Commander Defense Documentation Center ATTN: TIPCR Cameron Station Alexandria, Virginia 22314
1	Director of Defense Research and Engineering ATTN: Dir/Tech Info Washington, D. C. 20301
1	Director Advanced Research Projects Agency ATTN: Tech Info Department of Defense Washington, D. C. 20301
1	Commanding General U. S. Army Materiel Command ATTN: AMCDL Washington, D. C. 20315
1	Commanding General U. S. Army Materiel Command ATTN: AMCRD, Dr. J.V.R. Kaufman Washington, D. C. 20315
1	Commanding General U. S. Army Materiel Command ATTN: AMCRD-TE Washington, D. C. 20315
1	Commanding General U. S. Army Materiel Command ATTN: AMCRD-TP Washington, D. C. 20315
1	Commanding General U. S. Army Aviation Systems Command ATTN: AMSAV-E 12th and Spruce Streets St. Louis, Missouri 63166

No. of Copies	Organization
4	Commanding General U. S. Army Electronics Laboratories ATTN: AMSEL-RD-H AMSEL-HL-CT, Mr. Crossman AMSEL-XL, Dr. W. Pressman AMSEL-DL Fort Monmouth, New Jersey 07703
3	Commanding General U. S. Army Missile Command ATTN: AMSMI-R AMSMI-RBL AMSMI-RR, Dr. Lehnigk Redstone Arsenal, Alabama 35809
1	Commanding General U. S. Army Tank-Automotive Command ATTN: AMSTA-CL Warren, Michigan 48090
1	Commanding General U. S. Army Mobility Equipment Command ATTN: AMSME-R 4300 Goodfellow Boulevard St. Louis, Missouri 63120
1	Commanding Officer U. S. Army Mobility Equipment Research & Development Center ATTN: Tech Docu Cen, Bldg 315 Fort Belvoir, Virginia 22060
1	Commanding General U. S. Army Munitions Command ATTN: AMSMU-RE Dover, New Jersey 07801
1	Commanding General U. S. Army Electronic Proving Ground ATTN: Tech Lib Fort Huachuca, Arizona 85613

DISTRIBUTION LIST

No. of Copies	Organization
1	Commanding General U. S. Army Weapons Command ATTN: AMSWE-RE Rock Island, Illinois 61202
1	Commanding Officer U. S. Army Watervliet Arsenal ATTN: Dr. F. Schneider Watervliet, New York 12189
1	Commanding Officer U. S. Army Harry Diamond Laboratories ATTN: AMXDO-TD/002 Washington, D. C. 20438

2	Commanding General
	U. S. Army Natick Laboratories
	ATTN: Dr. E. Ross
	        AMXRE
	        Dr. Dale H. Sieling
	Natick, Massachusetts 01762

2	Commanding Officer
	U. S. Army Materials and
	  Mechanics Research Center
	ATTN: Dr. O. Bowie
	        AMXMR-ATL
	Watertown, Massachusetts 02172

1	Director U. S. Army Aeronautical Research Laboratory Moffett Naval Air Station California 94035
1	Commandant U. S. Army Command and General Staff College ATTN: Archives Fort Leavenworth, Kansas 66027
1	Mathematics Research Center U. S. Army University of Wisconsin Madison, Wisconsin 53706

No. of Copies	Organization
1	Deputy Assistant Secretary of the Army (R&D) Department of the Army Washington, D. C. 20315
1	Office of Vice Chief of Staff ATTN: CSAVCS-W-TIS Department of the Army Washington, D. C. 20315
4	Chief of Research & Development ATTN: CRDPES Dr. Watson Department of the Army Washington, D. C. 20310
3	Commander U. S. Naval Air Systems Command ATTN: AIR-604 Washington, D. C. 20360
3	Commander U. S. Naval Ordnance Systems Command ATTN: ORD-9132 Washington, D. C. 20360
2	Chief of Naval Research ATTN: Dr. L. Bram Code 402 Department of the Navy Washington, D. C. 20360
1	Commanding Officer and Director U. S. Navy Electronics Laboratory ATTN: Lib San Diego, California 92152
1	Director U. S. Naval Research Laboratory ATTN: Wave Propagation Br, Mr. Macdonald Washington, D. C. 20390

DISTRIBUTION LIST

No. of Copies	Organization

1 RADC (EMTLD, Lib)
Griffiss AFB
New York 13440

1 AUL (3T-AUL-60-118)
Maxwell AFB
Alabama 36112

1 Director
Environmental Science Service
Administration
U. S. Department of Commerce
Boulder, Colorado 80302

1 Director
National Aeronautics and
Space Administration
Electronics Research Center
ATTN: Comp Rsch Lab,
Dr. Van Meter
575 Technology Square
Cambridge, Massachusetts 02139

1 Director
Jet Propulsion Laboratory
ATTN: Lib (TDS)
4800 Oak Grove Drive
Pasadena, California 91103

1 Director
National Aeronautics and
Space Administration
Manned Spacecraft Center
ATTN: Lib
Houston, Texas 77058

1 President
Research Analysis Corporation
ATTN: Lib
McLean, Virginia 22101

1 Bell Telephone Laboratories
ATTN: Tech Docu Svcs
P. O. Box 2008
Ann Arbor, Michigan 48104

4 Brown University
ATTN: Dr. R. Clifton
Dr. H. Kolsky
Dr. A. Pipkin
Dr. L. Sirovich
Providence, Rhode Island 02912

3 University of California
ATTN: Dr. M. Carroll
Dr. J. Lubliner
Dr. J. Sackman
Berkeley, California 94720

1 University of California
Department of Mechanics
ATTN: Dr. R. Stern
Los Angeles, California 90024

1 University of California
Department of Aerospace and
Mech Engr Sciences
ATTN: Dr. S. Nemat-Nasser
P. O. Box 109
La Jolla, California 92037

1 California Institute of
Technology
Div of Engr & Appl Sc
ATTN: Dr. Miklowitz
1201 East California Boulevard
Pasadena, California 91102

1 Carnegie Institute of
Technology
Dept of Civil Engineering
ATTN: Dr. Walsh
Pittsburgh, Pennsylvania 15213

1 Cornell University
Department of Theoretical and
Applied Mechanics
ATTN: Dr. G. Ludford
Ithaca, New York 14850

29

DISTRIBUTION LIST

No. of Copies	Organization	No. of Copies	Organization
1	Forrestal Research Center Aeronautical Engineering Laboratory Princeton University ATTN: Dr. S. Lam Princeton, New Jersey 08540	13	Lehigh University ATTN: Dr. Venkataraman Dr. Varley (10 cys) Dr. Smith Dr. Beer Bethlehem, Pennsylvania 18015
1	Harvard University Division of Engineering and Applied Physics ATTN: Dr. G. Carrier Cambridge, Massachusetts 02138	3	Lehigh University ATTN: Dr. F. Erdogan Dr. G. Sih Dr. A. Kalnins Bethlehem, Pennsylvania 18015
1	The Johns Hopkins University ATTN: Dr. J. Ericksen 34th and Charles Streets Baltimore, Maryland 21218	2	Massachusetts Institute of Technology ATTN: Rsch Lab of Electronics Dr. Probstein 77 Massachusetts Avenue Cambridge, Massachusetts 02139
1	University of Kentucky ATTN: Dr. M. Beatty Dept of Engr Mech Lexington, Kentucky 40506	1	University of New Mexico Dept of Mech Engr ATTN: Dr. Feldman Albuquerque, New Mexico 87106
20	Lehigh University Center for the Application of Mathematics ATTN: Prof. R. Rivlin Bethlehem, Pennsylvania 18015	1	New York University Department of Mathematics ATTN: Dr. J. Keller University Heights New York, New York 10053
4	Lehigh University ATTN: Dr. P. Blythe Dr. A. Holz Dr. A. Kydoniefs Dr. G. McAllister Bethlehem, Pennsylvania 18015	1	North Carolina State University School of Engineering ATTN: Dr. Sun Chang Raleigh, North Carolina 27607
6	Lehigh University ATTN: Dr. M. Mortell Dr. E. Salathe Dr. T. Steel Dr. B. Seymour Dr. D. Edelen Dr. K. Sawyers Bethlehem, Pennsylvania 18015	1	Northwestern University Dept of Civil Engineering ATTN: Dr. S. Vogel Evanston, Illinois 60201

DISTRIBUTION LIST

No. of Copies	Organization	No. of Copies	Organization
1	Pennsylvania State University ATTN: E E Department 319 Electrical Engineering East University Park, Pennsylvania 16802	1	Rice University ATTN: Dr. R. Bowen P. O. Box 1892 Houston, Texas 77001
1	Pennsylvania State University College of Science ATTN: Dr. Kanwal 230 McAllister Building University Park, Pennsylvania 16802	2	Stanford Research Institute ATTN: Tech Lib Dr. H. Aggarwal 333 Ravenswood Avenue Menlo Park, California 94025

1	Purdue University
	Institute for Math Sciences
	ATTN: Dr. T. Mullikan
	        Dr. E. Cumberbatch
	Lafayette, Indiana 47907
		4	Yale University
			ATTN: Dr. J. Bleustein
			        Dr. B. Chu
			        Dr. E. Onat
			        Dr. Raeder
			400 Temple Street
			New Haven, Connecticut 96520

1	Rensselaer Polytechnic Institute Mechanics Department ATTN: Dr. J. Hawley Troy, New York 12181		Aberdeen Proving Ground C, Tech Lib Marine Corps Ln Ofc CDC Ln Ofc

DOCUMENT CONTROL DATA - R & D

Security classification of title, body of abstract and indexing annotation must be entered when the overall report is classified.

1. ORIGINATING ACTIVITY (Corporate author)	2a. REPORT SECURITY CLASSIFICATION
Center for the Application of Mathematics Lehigh University Bethlehem, Pennsylvania	Unclassified
	2b. GROUP

3. REPORT TITLE

Propagation of first-order electromagnetic discontinuities in an isotropic medium.

4. DESCRIPTIVE NOTES (Type of report and inclusive dates)

Unclassified Technical Report   February 1970

5. AUTHOR(S) (First name, middle initial, last name)

R. Venkataraman and R. S. Rivlin

6. REPORT DATE	7a. TOTAL NO. OF PAGES	7b. NO. OF REFS
February 1970	31	4

8a. CONTRACT OR GRANT NO.	9a. ORIGINATOR'S REPORT NUMBER(S)
DAD005-69-C-0053	
b. PROJECT NO.	CAM-110-9
Themis Project No. 65	
c.	9b. OTHER REPORT NO(S) (Any other numbers that may be assigned this report)
d.	BRL CR No. 7

10. DISTRIBUTION STATEMENT

This document has been approved for public release and sale; its distribution is unlimited.

11. SUPPLEMENTARY NOTES	12. SPONSORING MILITARY ACTIVITY
	U.S. Army Aberdeen Research & Development Ctr. Ballistic Research Laboratories Aberdeen Proving Ground, Maryland 21005

13. ABSTRACT

The propagation of a first-order electromagnetic discontinuity is discussed. Expressions are obtained for the possible velocities of propagation as functions of the field strengths ahead of the surface of discontinuity. Expressions are also obtained for the growth in the magnitude of the discontinuity as the wave progresses.

DD FORM 1473 (PAGE 1)

S/N 0101-807-6811

14. KEY WORDS	LINK A		LINK B		LINK C	
	ROLE	WT	ROLE	WT	ROLE	WT
electromagnetic waves, first-order discontinuity, non-linear materials, isotropy, growth of discontinuity.						